

# This is Why

- ▶ 152 CM DIAGONAL SCREEN SIZE
- ▶ 1.920 X 1.080 RESOLUTION IN DOTS
- ▶ INTEGRATED TOUCH SCREEN
- ▶ CONTRAST 4.000:1
- ▶ FULL WHITE LED BACKLIGHT
- ▶ EASY TO USE PEN SOFTWARE
- ▶ STREAMLINED COMMUNICATIONS VIA MFP CONNECTION
- ▶ MODUL SLOT SYSTEM



By integrating a 152 cm Sharp LCD monitor, a highly sensitive touch screen, and original user-intuitive pen software, Sharp has made the PN-L601B the ideal tool for meetings, video conferencing, presentations, corporate training, classroom lessons, and other applications where communication is key. The result is minimum effort and maximum work efficiency with this new touch-screen LCD monitor. BR>

## PANEL TYP

- ▶ Bildskärmsteknik: **TFT-LCD, UV<sup>2</sup>A**
- ▶ Skärmstorlek: **1.524 mm diagonal (60")**
- ▶ Optimal upplösning: **Full-HD 1920 x 1080 pixel**
- ▶ Färgversioner: **max. 1.064 Million (10 bit)**
- ▶ Ljusstyrka: **400 cd/m<sup>2</sup>**
- ▶ Kontrast: **4.000:1**
- ▶ Bezel H / V (mm): **(Touch Panel)**
- ▶ Responstid (ms): **6**
- ▶ Beträktningsvinke: **H/V 160°**

## DATA IN

- ▶ DVI-D in/ut: **yes (with Option PN-ZB01)**
- ▶ HDMI: ✓
- ▶ 15 Pin-Sub D (RGB H/V; Y/Ucb/Ucr): ✓

## PC - KONTROLL

- ▶ RS232C: ✓
- ▶ LAN: **yes (with Option PN-ZB01)**

## FÄRGSTANDARD

- ▶ PAL 60/N/M: ✓/✓/✓
- ▶ SECAM: ✓
- ▶ NTSC (MHz) 3.58/ 4.43: ✓/✓
- ▶ DTV 480i/480p/540p: ✓/✓/✓
- ▶ 576i/576p: ✓/✓
- ▶ 720p/1.035i: ✓/✓
- ▶ 1080i/1080p: ✓/✓
- ▶ 1080/24p: ✓/✓

## TILLBEHÖR

- ▶ Fjärrkontroll: ✓/✓
- ▶ Nätkabel / Signalkabel: ✓/✓

## PC - IN

- ▶ Full-HD (1920x1080): ✓
- ▶ UXGA 1600x1200: ✓
- ▶ SXGA+ 1400x1050: ✓
- ▶ SXGA 1280x1024: ✓
- ▶ WXGA 1280x800 / 1360x768 / 1366x768: ✓
- ▶ XGA 1024x768: ✓
- ▶ SVGA 800x600: ✓
- ▶ Mac Kompatibel: ✓

## VIDEO INGÅNG

- ▶ Composite (RCA/BNC): **yes BNC (with Option PN-ZB01)**
- ▶ S-Video (Y/C): **yes (with Option PN-ZB01)**
- ▶ DVI-D / DVI-I: ✓/no (with Option PN-ZB01)
- ▶ Component (RCA/BNC): **yes BNC (with Option PN-ZB01)**
- ▶ HDMI: ✓
- ▶ HDCP Kompatibel: ✓

## AUDIO TERMINALS

- ▶ Mini Jack (3.5 mm) in/out: ✓/X
- ▶ RCA-Stereo Terminal In/ut: ✓/yes (with Option PN-ZB01)
- ▶ Via HDMI-Terminal: ✓
- ▶ Ljud ut (W RMS): **Internal 2x 10W (Speaker Output 2x 10W; Option AN-ZB01)**

## INSTALLATION

- ▶ Stående/ Liggande: ✓/✓
- ▶ Vägghäste (mm): **VESA 200,4x M6 10mm 200x200,400x200**

## ÖVRIGT

- ▶ Fördelar: **Integrated touch screen solution OS: XP, Vista and Windows 7**
- ▶ Bild-i-bild-funktion: ✓
- ▶ DSPA (Data Signal Power Auto): ✓
- ▶ Strömförsörjning (V) / Effektbehov i aktivt läge (W) / Strömförsörjning, ECO (W) / Effektbehov i energisparläge (W): **100-240V/245W**
- ▶ Heat Dissipation (BTU / h): ECO-IMode / Standard: **836**
- ▶ Mått (bredd x höjd x djup): **1413 x 831 x 131**
- ▶ Vikt (kg): **51**
- ▶ EAN: **4974019679839**
- ▶ Effektförbrukning påläge (W), IEC 62087 Ed.2.0: **205.96**
- ▶ Effektförbrukning standby (W), IEC 62301 Ed.1.0: **0.37**
- ▶ Effektförbrukning fränläge (W), IEC 62301 Ed.1.0: **0**
- ▶ Kvoten för toppnivå av luminans för TV-mottager med fast meny (%): **80**
- ▶ Kvicksilver innehåll (mg): **0**
- ▶ Förekomst av bly: ✓

[www.sharp.se](http://www.sharp.se)

**SHARP**

SHARP ELECTRONICS (NORDIC) AB  
TELEFON 08 - 634 36 00  
[INFO.SE@SHARP.EU](mailto:INFO.SE@SHARP.EU)  
[WWW.SHARP.SE](http://WWW.SHARP.SE)